

# The Characteristic Sign Plate in Macau Suspension T5 Series

"JOHNSON" - SUPENSION series Emergency Exit / Directional Plate. Maintained type.

Application for practical and economical emergency luminaire,

suitable for surface / recessed mounted.

"強生牌"懸掛式系列緊急照明指示吊牌 ,設計以經濟實用爲原則, 適合明裝/暗藏天花安裝。

## **SPECIFICATION & TECHNICAL DATA**

規格及技術資料

#### NI-CD RECHARGEABLE BATTERY

MODEL 套件型號		JXP8R / SN2-Q	JXP14R / SN2-Q	
Internal Conversion Kit 內藏電池套件		JF8N2	JF14N2	
Wattage 適用瓦數	(W)	T5 / 8W	T5 / 14W	
Battery Capacity & Voltage 電池容量及電壓		5 x 1.8AH, 6V	5 x 1.8AH, 6V	
Emergency Output 緊急照明輸出流明		300 lumens	350 lumens	
Minimum Recharging Time 電池充滿所需時間	(h)	12 hours		

## NI-CD RECHARGEABLE BATTERY

MODEL 套件型號		JXP8R / SN3-Q	JXP14R / SN3-Q	
Internal W/P Fluo. fitting 內藏電池套件		JF8N3	JF14N3	
Wattage 適用瓦數	(W)	T5 / 8W	T5 / 14W	
Battery Capacity & Voltage 電池容量及電壓		5 x 2.5AH, 6V	5 x 2.5AH, 6V	
Emergency Output 緊急照明輸出流明		300 lumens	350 lumens	
Minimum Recharging Time 電池充滿所需時間	(h)	12 hours		
Dimension of Metal casing 吊牌箱呎吋 (LxHxD)	(mm)	440 x 120 x 70	670 x 120 x 70	
Dimension of Perspex 水晶吊牌呎吋 (LxHxT)	(mm)	400 x 200 x 9	550 x 200 x 9	
Signage Panel 燈箱膠片字樣及圖案		出SAIDA口, SAIDA出口 or Escape Route Sign		
Main Voltage / Frequency 市電(交流電)輸入電壓 / 頻率	(V)	A/C 220V ( + / - 10%) / 50Hz		
Emergency Starting Time 套件緊急照明啓動時間	(sec.)	< 0.3		
Operating Frequency 套件運作頻率	(kHz)	25~28		
Operating Temperature 套件運作環境溫度	(ta)	0℃ - 55 ℃		
Charge Indicator 充電指示		Red LED		
Test Button 測試掣		Press Type		
Low Voltage Protection 低壓截止保護線路		Electronic Protection (approx. 1V / cell)		
Compliance To 達致認可標準		BS 5266-1, BS EN 60598-2-22 and FSD PPA/104A(4th Revision)		
Guarantee Period 保用期	(M)	12 months		

Options: Sealed Ni-MH High Temp. Rechargeable Battery will be available on request.

: Clients can choose 30% or 50% lumen output when mains fail.

: R - Recessed mount; S - Surface mount



# JOHNSON



Self-contained emergency sign plate is used in Macau projects. It can be surface and recessed mount with single and double sided. The characters are depended on the clients needs.



JXP8R/SN3-T, 1x8W Emergency Sign plate with white escape signature with left directional arrow on green background.



JXP14R/SN3-Q, 1x14W Emergency Sign plate with white L/C in green background.



JXP8R/SN3-W

